

Teknisk specifikation Technical specifications

LIST OF CONTENTS	Page
Summary P 150 AST Operating instructions P 150 AST Summary P 150 Operating instructions P 150 To empty the coarse separator P 150 AST To change filter on model P 150 AST AND P 150 Fault-finding check list P 150 AST AND P 150 To change carbon brushes on model P 150 AST AND P 150 Technical data P 150 AST Technical data P 150 Spare parts list P 150 Wiring diagram P 150 AST	3 5 6 7 8 9 11 12 13 14 15-16 17-18 19 20
Wiring diagram P 150	20

ÖVERSIKT P 150 AST/SUMMARY P 150 AST

- 1. Bärhandtag/handle.
- Barranday/Handle.
 Grovavskiljare/Coarse separator.
 3-läges strömbrytare (man. 0 auto)/ Switch with 3 positions (manual on/off automatic).
 Indicator for position "Auto".
 Indicator for position "Filter full".

- 6. Holder for welding or welding return cable.
- 7. Exhaust.
- 8. Filter indicator hose.
- 9. Sensor for automatic.




Bild 1/Picture 1

OPERATING INSTRUCTIONS P 150 AST

CARRYVAC P 150 AST welding fume eliminator has two operating modes, either manual or automatic.

Manual mode:

Switch (3), picture 1 on page 3, to "Man" position. The unit will now function continuously.

Automatic mode:

Switch (3), picture 1 on page 3, to "Auto" position. Place the welding cable, or welding return cable in the cable holder, see picture 2. The unit will now function when the welding arc i struck and cease operation when the arc is broken.


If welding at a low current, it might be necessary to loop the cable several times through the holder with the sensor, see picture 3.

For certain types of welding, for example TIG, the elctronics may have some difficulty in registrating the welding current through the cable holder.

Indicator light:


"Auto" (4), picture 1 on page 3, indicates that the current supply to the electronics is operative.

"Filter" (5), picture 1 on page 3, indicates that the filter is full with welding fume particulate, and requires changing as soon as possible to ensure maximum suction effectiveness.



ÖVERSIKT P 150/SUMMARY P 150

- Bärhandtag/Handle.
 Grovavskiljare/Coarse separator.
 Strömbrytare/Switch.
 Indikering för fullt filter/Indicator for "Filter full".
 Utblås/Exhaust.
 Slang för filterindikering/Filter indicator hose.



OPERATING INSTRUCTIONS

CARRYVAC P 150 welding fume eliminator has one operating mode, manual. The operation is started and stopped by the switch (3), picture 4 on page 6.

Indicator lights:

"Filter" (4), picture 4 on page 6, indicates that the filter is full with welding fume particulate and requires changing as soon as possible to ensure maximum suction effectiveness.

TO EMPTY THE COARSE SEPARATOR MODEL P 150 AST AND P 150


The coarse separator ususally needs to be emptied only when the filter is changed, but heavy use of some types of electrodes may call for more frequent emptying.

How to do it:

See picture 5.

Switch off the fume eliminator, remove the suction hose (1) adn the indicator hose (2) from the coarse separator. Lift the lock handle (3) to release the coarse separator (4). Unscrew locking screw (5), remove the cover from the gable for emptying.

N.B.! Check rubber seal around the cover for any signs of damage before reassembly to ensure maximum suction efficiency.




TO CHANGE FILTER ON MODEL P 150 AST AND P 150

A new filter needs to be fitted when the suction becomes inadequate, or the indicator lamp is showing "Filter".

How to do it:

- 1. Switch off the unit.
- 2. Remove the filter indicator hose and the suction hose, picture 5 on page 8.
- 3. Lift the lock handle and remove the coarse separator, picture 5 on page 8.
 4. Pull out and dispose the old filter, picture 6.
- 5. Insert a new filter.
- 6. Empty the coarse separator, picture 5 on page 8.



FAULT-FINDING CHECK LIST

N.B.! Remove plug from electricity supply before carrying our any work (on electricity unit). Furthermore, all operation should be carried out by a qualified electrician.

Fault:

Poor suction.

Check:

- hose and connections are tight
- the control lamp "Filter" does not lightthe hose is not blocked

Fault:

Motor failure.

Check:

- current is reaching the unit
- the carbon brushes

Fault:

The unit does not start in position "Auto" (P 150 AST).

Check:

- the welding cable is fitted in the cable holder
- the control lamp for "Auto" lights
- put the cable through the cable holder twice, see picture 3 on page 5.

If the fault remains:

- contact your supplier.


TO CHANGE CARBON BRUSHES P 150 AST AND P 150

N.B.I Remove plug from electricity supply before carrying our any work (on electricity unit). Furthermore, all operation should be carried out by a qualified electrician.

How to do it:

See picture 7.

Remove the cooling air gable by loosening 4 screws in the frame. Remove the pressure guard hoses for the filter indication. Remove the cables. N.B.I Care should be taken when re-fitting the cables and hoses. The carbon brushes are now available for changing. Instructions for fitting are included with every brush set. If necessary contact you supplier.



TECHNICAL DATA P 150

Lenth
Width
Height
Weight inclusive filter
Voltage
(also available for 110 V)
Efficiency
Max. vacuum
Air flow unit with
3.0 m hose 45 mm dia.
Noise level
Hose standard
Active filier surface
Separation degree

860 mm 226 mm 425 mm 16 kg 220 V

1000 W 2170 mm wg

150 m³/h 75 dB(A) 3.0 m₄5 m dia. 5.3 m² 99.7 %

TECHNICAL DATA P 150 AST

Lenth
Width
Height
Weight inclusive filter
Voltage
(also available for 110 V)
Efficiency
Max. vacuum
Air flow unit with
3.0 m hose 45 mm dia.
Noise level
Hose standard
Volve filter socialed
Separation degree


860 mm 226 mm 425 mm 16 kg 220 V

1000 W 2170 mm wg

150 m³/h 75 dB(A)


3.0 m,45 mm dia.

99.7 %



RESERVDELSLISTA/SPARE PARTS LIST CARRYVAC P 150 AST

Pos	Art No	Designation
1 1 1 1 2 3 4 5	154352015 154352008 154352006 154352002 468455004 468455010 468455011 468455012	Flexible hose 1.6 m 45 mm dia. Flexible hose 3.5 m 45 mm dia. Flexible hose 5.0 m 45 mm dia. Flexible hose 15.0 m 45 mm dia. Hose connection Knob for coarse separator Cover for coarse separator Cover plate for metal filter (accessory) Metal filter (accessory)
7 8	468455013 846455014	Inner gable for coarse separator Coarse separator complete (Pos 3, 4, 7)
9 10 11 13 14 15 16 17 18 19 20 21 22 23 24 25 27 28 29 30 31 32	468455015 468455016 468455017 468455018 468455019 468455036 468455020 468455021 468455023 468455023 468455024 468455025 468455026 468455027 468455028 468455029 468455030 468455031 468455031 468455033 468455034 468455035	Filter Filter cover Top cover Handle Hose for filter indicator Plastic frame Motor gable Packing set (3 pcs) Motor 220 V Motor 110 V Carbon brushes 220 V Carbon brushes 110 V Motor cover Sound proofing PC-Board AST Pressure guard Cooling air gable Locking washer Cable holder Indicator lamp "Auto" and "Filter" Lens "Auto" Switch Lens "Filter" Radio filter (for certain countries only)



RESERVDELSLISTA/SPARE PARTS LIST CARRYVAC P 150

Pos Art No Designation 1			
1 154352008	Pos	Art No	Designation
8 468455014 Coarse separator complete (Pos 3, 4, 7) Filter Filter cover Top cover Handle Hose for filter indicator Plastic frame Motor gable Packing set (3 pcs) Motor 110 V Carbon brushes 220 V Carbon brushes 110 V Motor cover Carbon brushes 110 V Motor cover Motor cover Motor cover Sound proofing Pressure guard Cooling air gable Indicator lamp "Filter" Switch Lens "Filter" Radio filter	1 1 1 2 3 4 5	154352008 154352006 154352002 468455004 468455010 028500800 468455012	Flexible hose 3.5 m 45 mm dia. Flexible hose 5.0 m 45 mm dia. Flexible hose 15.0 m 45 mm dia. Hose connection Knob for coarse separator Cover for coarse separator Cover plate for metal filter (accessory) Metal filter (accessory)
9 468455001 Filter 10 468455015 Filter cover 11 468455016 Top cover 12 468455017 Handle 13 468455018 Hose for filter indicator 15 468455036 Motor gable 16 468455020 Packing set (3 pcs) 17 468455021 Motor 220 V 18 468455022 Motor 110 V 19 468455038 Carbon brushes 220 V 20 468455038 Carbon brushes 110 V 21 468455024 Motor cover 22 468455025 Sound proofing 23 468455027 Pressure guard 24 468455039 Cooling air gable 25 468455031 Indicator lamp "Filter" 28 468455035 Radio filter	8		Coarse separator complete
27 468455034 Lens "Filter" 28 468455035 Radio filter	10 11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26	468455015 468455016 468455017 468455018 468455019 468455020 468455021 468455022 468455023 468455023 468455025 468455025 468455025 468455039 468455031	Filter Filter cover Top cover Handle Hose for filter indicator Plastic frame Motor gable Packing set (3 pcs) Motor 220 V Motor 110 V Carbon brushes 220 V Carbon brushes 110 V Motor cover Sound proofing Pressure guard Cooling air gable Indicator lamp "Filter"

